

GFCI SINGLE OUTLET ADAPTER, 3-WIRE



30339005

Tower's GFCI Single Outlet Adapter 3-wire

Model 30339005 can be used to convert any standard indoor electrical outlet into a ground fault (GFCI) protected outlet.

This light weight, portable product can be used in the home, office, vacation cabin or workshop.

The bright “Red” light indicates when the power is “ON”. The TEST and RESET buttons allow for periodic testing.

FEATURES

MODEL 30339005

- **Compatible with 15 amp U-ground outlets and plugs, 2 or 3 wire**
- **Trip level 4-6 mA**
- **UL and CUL listed**
- **Automatic reset**
- **Rated for indoor use only**

SPECIFICATIONS

- **Class “A” people protection GFCI**
- **Rated for 125 volt, 15 amp use**
- **1875 watts, 60 Hz**
- **LED Power “ON” indicator**
- **Open neutral and ground neutral protection**
- **Operating temperature range -35 degree C to 66 degree C**
- **Impact resistant case**

SIMILAR MODELS

**MODEL 30340001
SINGLE OUTLET GFCI
ADAPTER 2 WIRE,
NO U-GROUND**

**MODEL 30339015
5 OUTLET GFCI
ADAPTER**